## **SIEMENS**

## **Data sheet**

## 3RA2155-4PA35-0AK6

|  | Fuseless motor starter Direct start 600VAC Size S2 28-36A 110/120VAC 50/60HZ screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) |
|--|---|
|  | 1NO+1NC (contactor)   |
| product brand name   | SIRIUS  |
| product designation  | non-fused motor starter 3RA2  |
| design of the product  | direct starter  |
| manufacturer's article number  |   |
| of the supplied contactor  | 3RT2035-1AK60   |
| <ul> <li>of the supplied circuit-breakers</li> </ul>   | 3RV2032-4PA15   |
| <ul> <li>of the supplied link module</li> </ul>  | 3RA2931-1AA00   |
| General technical data   |   |
| size of the circuit-breaker  | S2  |
| size of load feeder  | S2  |
| product extension auxiliary switch   | Yes   |
| insulation voltage with degree of pollution 3 at AC rated value  | 690 V   |
| degree of pollution  | 3   |
| surge voltage resistance rated value   | 6 kV  |
| shock resistance according to IEC 60068-2-27   | 6g / 11 ms  |
| mechanical service life (operating cycles) of contactor typical  | 10 000 000  |
| type of assignment   | 2   |
| Ambient conditions   |   |
| ambient temperature  |   |
| during operation   | -20 +60 °C  |
| during storage   | -50 +80 °C  |
| during transport   | -55 +80 °C  |
| Main circuit   |   |
|  |   |
| number of poles for main current circuit   | 3   |
| number of poles for main current circuit  design of the switching contact  | _ 3<br>electromechanical  |
| design of the switching contact adjustable current response value current of the current-  | electromechanical 28 36 A   |
| design of the switching contact adjustable current response value current of the current- dependent overload release   | electromechanical   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage   | electromechanical 28 36 A   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value   | electromechanical 28 36 A 690 V   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum  | electromechanical 28 36 A  690 V 690 V  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum operating frequency rated value  | electromechanical 28 36 A  690 V 690 V 50 60 Hz   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value   | electromechanical 28 36 A  690 V 690 V  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3  | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value   | electromechanical 28 36 A  690 V 690 V 50 60 Hz   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value Control circuit/ Control   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value  Control circuit/ Control control supply voltage at AC • at 50 Hz rated value   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value  Control circuit/ Control control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value  | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value  Control circuit/ Control  control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value • at 60 Hz rated value   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value  Control circuit/ Control  control supply voltage at AC • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value  apparent holding power of magnet coil at AC   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA   |
| design of the switching contact adjustable current response value current of the current- dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V   |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value  Control circuit/ Control  control supply voltage at AC • at 50 Hz rated value • at 50 Hz rated value • at 60 Hz rated value • at 60 Hz rated value apparent holding power of magnet coil at AC inductive power factor with the holding power of the coil  Auxiliary circuit  | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |
| design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |
| design of the switching contact adjustable current response value current of the current- dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts   | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |
| design of the switching contact adjustable current response value current of the current- dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions             | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |
| design of the switching contact adjustable current response value current of the current- dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions  trip class | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |
| design of the switching contact adjustable current response value current of the current- dependent overload release  operating voltage  • rated value • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  Control circuit/ Control  control supply voltage at AC  • at 50 Hz rated value  • at 50 Hz rated value  • at 60 Hz rated value  • at 60 Hz rated value  apparent holding power of magnet coil at AC  inductive power factor with the holding power of the coil  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions             | electromechanical 28 36 A  690 V 690 V 50 60 Hz 35 A  18 500 W  110 V 88 121 V 120 V 96 132 V 16 VA 0.37  |

| UL/CSA ratings   |           |   |                           |  |  |
|--|-----------|---|---------------------------|--|--|
| yielded mechanical performance [hp]  |           |   |                           |  |  |
| for single-phase AC motor  |           |   |                           |  |  |
| — at 110/120 V rated value   | 3 hp      |   |                           |  |  |
| • for 3-phase AC motor   | ·p        |   |                           |  |  |
| — at 200/208 V rated value   | 10 hp     |   |                           |  |  |
| Short-circuit protection   |           |   |                           |  |  |
| product function short circuit protection  | Yes       |   |                           |  |  |
| design of the short-circuit trip   | magnetic  |   |                           |  |  |
| conditional short-circuit current (Iq)   |           |   |                           |  |  |
| at 400 V according to IEC 60947-4-1 rated value  | 150 000 A |   |                           |  |  |
| Installation/ mounting/ dimensions   |           |   |                           |  |  |
| mounting position  | vertic    | vertical  |                           |  |  |
| fastening method   | Snap      | Snap-mounted to DIN rail or screw-mounted with additional push-in lug |                           |  |  |
| height   | 274 r     | 274 mm  |                           |  |  |
| width  | 55 m      | 55 mm   |                           |  |  |
| depth  | 150 r     | 150 mm  |                           |  |  |
| required spacing   |           |   |                           |  |  |
| <ul> <li>for grounded parts</li> </ul>   |           |   |                           |  |  |
| — forwards   | 0 mm      | ı   |                           |  |  |
| — backwards  | 0 mm      | 0 mm  |                           |  |  |
| — upwards  | 50 m      | 50 mm   |                           |  |  |
| — at the side  | 10 mm     |   |                           |  |  |
| — downwards  | 10 mm     |   |                           |  |  |
| • for live parts   |           |   |                           |  |  |
| — forwards   | 0 mm      |   |                           |  |  |
| — backwards  | 0 mm      |   |                           |  |  |
| — upwards  | 50 mm     |   |                           |  |  |
| — downwards  | 10 mm     |   |                           |  |  |
| — at the side  | 10 m      | 10 mm   |                           |  |  |
| Connections/ Terminals   |           |   |                           |  |  |
| type of electrical connection for main current circuit   |           | screw-type terminals  |                           |  |  |
| type of connectable conductor cross-sections for main contacts stranded                        | 1 5       | 1 50 mm², 2x (1 25 mm²)   |                           |  |  |
| connectable conductor cross-section for main contacts finely stranded with core end processing | 1 3       | 1 35 mm²  |                           |  |  |
| Safety related data  |           |   |                           |  |  |
| B10 value with high demand rate according to SN 31920  | 1 000     | 1 000 000   |                           |  |  |
| proportion of dangerous failures with high demand rate according to SN 31920                   | 73 %      | 73 %  |                           |  |  |
| protection class IP on the front according to IEC 60529  | IP20      | IP20  |                           |  |  |
| touch protection on the front according to IEC 60529   | finge     | finger-safe, for vertical contact from the front                      |                           |  |  |
| Certificates/ approvals  |           |   |                           |  |  |
| General Product Approval   |           | For use in hazard-<br>ous locations                                   | Declaration of Conformity |  |  |

Confirmation











**Test Certificates** 

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway Dangerous Good







Confirmation Vibration and Shock Transport Information

## **Further information**

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2155-4PA35-0AK6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2155-4PA35-0AK6

 ${\bf Service \& Support\ (Manuals,\ Certificates,\ Characteristics,\ FAQs,...)}$ 

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4PA35-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2155-4PA35-0AK6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4PA35-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2155-4PA35-0AK6&objecttype=14&gridview=view1

| last modified: | 12/15/2020 🖸 |
|----------------|--------------|
|                |              |